





SCRs

(Continued)

I_T (AMPS)	0.8						
@ T_C (°C)	60	60	60	60	60	60	60
I_{TSM} (AMPS)	10	10	10	10	10	10	10
CASE	 TO-92 Pinout C G A	 TO-92 Pinout A G C	 TO-92 Pinout A G C			 TO-92 Pinout C G A	
V_{RRM} (VOLTS)							
30	2N5060	BRX44*	C103Y*	–	–	–	–
60	2N5061	BRX45*	C103YY*	–	–	–	–
100	2N5062	BRX46*	C103A*	–	–	–	–
150	2N5063	–	–	–	–	–	–
200	2N5064	BRX47*	C103B*	CS55B*	CS55BZ*	CS92B	CS92BZ
300	2N6564	BRX48*	–	–	–	–	–
400	2N6565	BRX49*	–	CS55D*	CS55DZ*	CS92D	CS92DZ
600	–	–	–	–	–	CS92M	CS92MZ
800	–	–	–	–	–	CS92N	CS92NZ
I_{GT}	200 μ A	200 μ A	200 μ A	200 μ A	20 μ A	200 μ A	20 μ A
V_{GT}	0.8V	0.8V	0.8V	0.8V	0.8V	0.8V	0.8V
I_H	5.0mA	5.0mA	5.0mA	5.0mA	5.0mA	5.0mA	5.0mA

* TO-92-18R lead forming available. Please consult factory.

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms